

Symbols for Legacy Computing

Range: 1FB00–1FBFF

This file contains an excerpt from the character code tables and list of character names for *The Unicode Standard, Version 17.0 BETA REVIEW DRAFT*

This file may be changed at any time without notice to reflect errata, or other updates to the Unicode Standard.

See <https://www.unicode.org/errata/> for an up-to-date list of errata.

See <https://www.unicode.org/charts/> for access to a complete list of the latest character code charts. See <https://www.unicode.org/charts/PDF/Unicode-17.0/> for charts showing only the characters added in Unicode 17.0. See <https://www.unicode.org/Public/17.0.0/charts/> for a complete archived file of character code charts for Unicode 17.0. See <https://www.unicode.org/charts/About.html#Conventions> for conventions used in these code charts, and other general information.

Disclaimer

These charts are provided as the online reference to the character contents of the Unicode Standard, Version 17.0 but do not provide all the information needed to fully support individual scripts using the Unicode Standard. For a complete understanding of the use of the characters contained in this file, please consult the appropriate sections of The Unicode Standard, Version 17.0, online at <https://www.unicode.org/versions/Unicode17.0.0/>, as well as the Unicode Standard Annexes, the other Unicode Technical Reports and Standards, and the Unicode Character Database, which are available online.

See <https://www.unicode.org/ucd/> and <https://www.unicode.org/reports/>

A thorough understanding of the information contained in these additional sources is required for a successful implementation.

Fonts

The shapes of the reference glyphs used in these code charts are not prescriptive. Considerable variation is to be expected in actual fonts.

See <https://www.unicode.org/charts/fonts.html> for a list.

Terms of Use

© 1991–2025 Unicode, Inc. This publication is protected by copyright, and permission must be obtained from Unicode, Inc. prior to any reproduction, modification, or other use not permitted by the Terms of Use (<https://www.unicode.org/copyright.html>). Specifically, you may make copies of this publication and may annotate and translate it solely for personal or internal business purposes and not for public distribution, provided that any such permitted copies and modifications fully reproduce all copyright and other legal notices contained in the original. You may not make copies of or modifications to this publication for public distribution, or incorporate it in whole or in part into any product or publication without the express written permission of Unicode.

The Unicode Consortium specifically grants ISO a license to produce such code charts with their associated character names list to show the repertoire of characters for that standard, as a normatively referenced, integral part of that standard.

Unicode uses most fonts under restricted license from the original font owner. You may not extract, copy, modify, or distribute fonts or font data from any Unicode Products, including this publication, without license from the font owner.

Use of all Unicode Products, including this publication, is governed by the Unicode Terms of Use

(<https://www.unicode.org/copyright.html>). The authors, contributors, and publishers have taken care in the preparation of this publication, but make no express or implied representation or warranty of any kind and assume no responsibility or liability for errors or omissions or for consequential or incidental damages that may arise therefrom. This publication is provided “AS-IS” without charge as a convenience to users.

Unicode and the Unicode Logo are registered trademarks of Unicode, Inc., in the United States and other countries.

	1FB0	1FB1	1FB2	1FB3	1FB4	1FB5	1FB6	1FB7	1FB8	1FB9	1FBA	1FBB	1FBC	1FBD	1FBE	1FBF
0																
1																
2																
3																
4																
5																
6																
7																
8																
9																
A																
B																
C																
D																
E																
F																

Block mosaic terminal graphic characters

The term "sextant" refers to block mosaics divided into six parts.

1FB00	█	BLOCK SEXTANT-1
1FB01	█	BLOCK SEXTANT-2
1FB02	█	BLOCK SEXTANT-12
		• upper one third block
1FB03	█	BLOCK SEXTANT-3
1FB04	█	BLOCK SEXTANT-13
1FB05	█	BLOCK SEXTANT-23
1FB06	█	BLOCK SEXTANT-123
1FB07	█	BLOCK SEXTANT-4
1FB08	█	BLOCK SEXTANT-14
1FB09	█	BLOCK SEXTANT-24
1FB0A	█	BLOCK SEXTANT-124
1FB0B	█	BLOCK SEXTANT-34
		• middle one third block
1FB0C	█	BLOCK SEXTANT-134
1FB0D	█	BLOCK SEXTANT-234
1FB0E	█	BLOCK SEXTANT-1234
		• upper two thirds block
1FB0F	█	BLOCK SEXTANT-5
1FB10	█	BLOCK SEXTANT-15
1FB11	█	BLOCK SEXTANT-25
1FB12	█	BLOCK SEXTANT-125
1FB13	█	BLOCK SEXTANT-35
1FB14	█	BLOCK SEXTANT-235
1FB15	█	BLOCK SEXTANT-1235
1FB16	█	BLOCK SEXTANT-45
1FB17	█	BLOCK SEXTANT-145
1FB18	█	BLOCK SEXTANT-245
1FB19	█	BLOCK SEXTANT-1245
1FB1A	█	BLOCK SEXTANT-345
1FB1B	█	BLOCK SEXTANT-1345
1FB1C	█	BLOCK SEXTANT-2345
1FB1D	█	BLOCK SEXTANT-12345
1FB1E	█	BLOCK SEXTANT-6
1FB1F	█	BLOCK SEXTANT-16
1FB20	█	BLOCK SEXTANT-26
1FB21	█	BLOCK SEXTANT-126
1FB22	█	BLOCK SEXTANT-36
1FB23	█	BLOCK SEXTANT-136
1FB24	█	BLOCK SEXTANT-236
1FB25	█	BLOCK SEXTANT-1236
1FB26	█	BLOCK SEXTANT-46
1FB27	█	BLOCK SEXTANT-146
1FB28	█	BLOCK SEXTANT-1246
1FB29	█	BLOCK SEXTANT-346
1FB2A	█	BLOCK SEXTANT-1346
1FB2B	█	BLOCK SEXTANT-2346
1FB2C	█	BLOCK SEXTANT-12346
1FB2D	█	BLOCK SEXTANT-56
		• lower one third block
1FB2E	█	BLOCK SEXTANT-156
1FB2F	█	BLOCK SEXTANT-256
1FB30	█	BLOCK SEXTANT-1256
		• upper and lower one third block
1FB31	█	BLOCK SEXTANT-356
1FB32	█	BLOCK SEXTANT-1356
1FB33	█	BLOCK SEXTANT-2356
1FB34	█	BLOCK SEXTANT-12356

1FB35	█	BLOCK SEXTANT-456
1FB36	█	BLOCK SEXTANT-1456
1FB37	█	BLOCK SEXTANT-2456
1FB38	█	BLOCK SEXTANT-12456
1FB39	█	BLOCK SEXTANT-3456
		• lower two thirds block
1FB3A	█	BLOCK SEXTANT-13456
1FB3B	█	BLOCK SEXTANT-23456

Smooth mosaic terminal graphic characters

1FB3C	▤	LOWER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER CENTRE
1FB3D	▥	LOWER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER RIGHT
1FB3E	▦	LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER CENTRE
1FB3F	▧	LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER RIGHT
1FB40	▨	LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO LOWER CENTRE
1FB41	▩	LOWER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER CENTRE
1FB42	▪	LOWER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER RIGHT
1FB43	▫	LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER CENTRE
1FB44	▬	LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER RIGHT
1FB45	▭	LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO UPPER CENTRE
1FB46	▮	LOWER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER MIDDLE RIGHT
1FB47	▯	LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO LOWER MIDDLE RIGHT
1FB48	▰	LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO LOWER MIDDLE RIGHT
1FB49	▱	LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO UPPER MIDDLE RIGHT
1FB4A	▲	LOWER RIGHT BLOCK DIAGONAL LOWER LEFT TO UPPER MIDDLE RIGHT
1FB4B	△	LOWER RIGHT BLOCK DIAGONAL LOWER CENTRE TO UPPER RIGHT
1FB4C	▴	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO UPPER MIDDLE RIGHT
1FB4D	▵	LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO UPPER MIDDLE RIGHT
1FB4E	▶	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO LOWER MIDDLE RIGHT
1FB4F	▷	LOWER LEFT BLOCK DIAGONAL UPPER LEFT TO LOWER MIDDLE RIGHT
1FB50	▸	LOWER LEFT BLOCK DIAGONAL UPPER CENTRE TO LOWER RIGHT
1FB51	▹	LOWER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER MIDDLE RIGHT
1FB52	►	UPPER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER CENTRE
1FB53	▻	UPPER RIGHT BLOCK DIAGONAL LOWER MIDDLE LEFT TO LOWER RIGHT
1FB54	▼	UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER CENTRE
1FB55	▽	UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER RIGHT
1FB56	▾	UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO LOWER CENTRE
1FB57	▿	UPPER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER CENTRE

1FB58		UPPER LEFT BLOCK DIAGONAL UPPER MIDDLE LEFT TO UPPER RIGHT
1FB59		UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER CENTRE
1FB5A		UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER RIGHT
1FB5B		UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO UPPER CENTRE
1FB5C		UPPER LEFT BLOCK DIAGONAL LOWER MIDDLE LEFT TO UPPER MIDDLE RIGHT
1FB5D		UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO LOWER MIDDLE RIGHT
1FB5E		UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO LOWER MIDDLE RIGHT
1FB5F		UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO UPPER MIDDLE RIGHT
1FB60		UPPER LEFT BLOCK DIAGONAL LOWER LEFT TO UPPER MIDDLE RIGHT
1FB61		UPPER LEFT BLOCK DIAGONAL LOWER CENTRE TO UPPER RIGHT
1FB62		UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO UPPER MIDDLE RIGHT
1FB63		UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO UPPER MIDDLE RIGHT
1FB64		UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO LOWER MIDDLE RIGHT
1FB65		UPPER RIGHT BLOCK DIAGONAL UPPER LEFT TO LOWER MIDDLE RIGHT
1FB66		UPPER RIGHT BLOCK DIAGONAL UPPER CENTRE TO LOWER RIGHT
1FB67		UPPER RIGHT BLOCK DIAGONAL UPPER MIDDLE LEFT TO LOWER MIDDLE RIGHT
1FB68		UPPER AND RIGHT AND LOWER TRIANGULAR THREE QUARTERS BLOCK
1FB69		LEFT AND LOWER AND RIGHT TRIANGULAR THREE QUARTERS BLOCK
1FB6A		UPPER AND LEFT AND LOWER TRIANGULAR THREE QUARTERS BLOCK
1FB6B		LEFT AND UPPER AND RIGHT TRIANGULAR THREE QUARTERS BLOCK
1FB6C		LEFT TRIANGULAR ONE QUARTER BLOCK
1FB6D		UPPER TRIANGULAR ONE QUARTER BLOCK
1FB6E		RIGHT TRIANGULAR ONE QUARTER BLOCK
1FB6F		LOWER TRIANGULAR ONE QUARTER BLOCK

Block elements

1FB70		VERTICAL ONE EIGHTH BLOCK-2 → 258F
1FB71		VERTICAL ONE EIGHTH BLOCK-3
1FB72		VERTICAL ONE EIGHTH BLOCK-4
1FB73		VERTICAL ONE EIGHTH BLOCK-5
1FB74		VERTICAL ONE EIGHTH BLOCK-6
1FB75		VERTICAL ONE EIGHTH BLOCK-7 → 2595
1FB76		HORIZONTAL ONE EIGHTH BLOCK-2 → 2594
1FB77		HORIZONTAL ONE EIGHTH BLOCK-3
1FB78		HORIZONTAL ONE EIGHTH BLOCK-4
1FB79		HORIZONTAL ONE EIGHTH BLOCK-5
1FB7A		HORIZONTAL ONE EIGHTH BLOCK-6
1FB7B		HORIZONTAL ONE EIGHTH BLOCK-7 → 2581
1FB7C		LEFT AND LOWER ONE EIGHTH BLOCK
1FB7D		LEFT AND UPPER ONE EIGHTH BLOCK
1FB7E		RIGHT AND UPPER ONE EIGHTH BLOCK

1FB7F		RIGHT AND LOWER ONE EIGHTH BLOCK
1FB80		UPPER AND LOWER ONE EIGHTH BLOCK

Window title bar

This character is a legacy graphic used to draw the title bar of the active window. The lines corresponding to 3 and 5 are not actually block elements, but can show any horizontally repeating pattern.

1FB81		HORIZONTAL ONE EIGHTH BLOCK-1358
-------	--	----------------------------------

Block elements

1FB82		UPPER ONE QUARTER BLOCK → 2582
1FB83		UPPER THREE EIGHTHS BLOCK → 2583
1FB84		UPPER FIVE EIGHTHS BLOCK → 2585
1FB85		UPPER THREE QUARTERS BLOCK → 2586
1FB86		UPPER SEVEN EIGHTHS BLOCK → 2587
1FB87		RIGHT ONE QUARTER BLOCK → 258E
1FB88		RIGHT THREE EIGHTHS BLOCK → 258D
1FB89		RIGHT FIVE EIGHTHS BLOCK → 258B
1FB8A		RIGHT THREE QUARTERS BLOCK → 258A
1FB8B		RIGHT SEVEN EIGHTHS BLOCK → 2589

Rectangular shade characters

1FB8C		LEFT HALF MEDIUM SHADE
1FB8D		RIGHT HALF MEDIUM SHADE
1FB8E		UPPER HALF MEDIUM SHADE
1FB8F		LOWER HALF MEDIUM SHADE
1FB90		INVERSE MEDIUM SHADE → 2592
1FB91		UPPER HALF BLOCK AND LOWER HALF INVERSE MEDIUM SHADE
1FB92		UPPER HALF INVERSE MEDIUM SHADE AND LOWER HALF BLOCK
1FB93		<reserved>
1FB94		LEFT HALF INVERSE MEDIUM SHADE AND RIGHT HALF BLOCK

Fill characters

1FB95		CHECKER BOARD FILL → 259A
		→ 1F67F
1FB96		INVERSE CHECKER BOARD FILL → 259E
		→ 1F67E
1FB97		HEAVY HORIZONTAL FILL • upper middle and lower one quarter block → 3013
		→ 1CDB7

Diagonal fill characters

The filled area for these diagonal fill characters typically covers between one quarter and one half the total area. The diagonal lines should be of uniform width.

- 1FB98  UPPER LEFT TO LOWER RIGHT FILL
→ 25A7  square with upper left to lower right fill
- 1FB99  UPPER RIGHT TO LOWER LEFT FILL
→ 25A8  square with upper right to lower left fill

Smooth mosaic terminal graphic characters

- 1FB9A  UPPER AND LOWER TRIANGULAR HALF BLOCK
→ 29D7  black hourglass
- 1FB9B  LEFT AND RIGHT TRIANGULAR HALF BLOCK
→ 29D3  black bowtie

Triangular shade characters

- 1FB9C  UPPER LEFT TRIANGULAR MEDIUM SHADE
→ 25E4  black upper left triangle
- 1FB9D  UPPER RIGHT TRIANGULAR MEDIUM SHADE
→ 25E5  black upper right triangle
- 1FB9E  LOWER RIGHT TRIANGULAR MEDIUM SHADE
→ 25E2  black lower right triangle
- 1FB9F  LOWER LEFT TRIANGULAR MEDIUM SHADE
→ 25E3  black lower left triangle

Character cell diagonals

- 1FBA0  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT
- 1FBA1  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT
- 1FBA2  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER CENTRE
- 1FBA3  BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO LOWER CENTRE
- 1FBA4  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE
- 1FBA5  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE
- 1FBA6  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER CENTRE TO MIDDLE RIGHT
- 1FBA7  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO UPPER CENTRE TO MIDDLE RIGHT
- 1FBA8  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT AND MIDDLE RIGHT TO LOWER CENTRE
- 1FBA9  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT AND MIDDLE LEFT TO LOWER CENTRE
- 1FBAA  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE TO MIDDLE LEFT
- 1FBAB  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE TO MIDDLE RIGHT
- 1FBAC  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO UPPER CENTRE TO MIDDLE RIGHT TO LOWER CENTRE
- 1FBAD  BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO UPPER CENTRE TO MIDDLE LEFT TO LOWER CENTRE
- 1FBAE  BOX DRAWINGS LIGHT DIAGONAL DIAMOND
→ 25C7  white diamond

Light solid line with stroke

- 1FBAF  BOX DRAWINGS LIGHT HORIZONTAL WITH VERTICAL STROKE
→ 2500  box drawings light horizontal

Terminal graphic characters

- 1FBB0  ARROWHEAD-SHAPED POINTER
→ 27A4  black rightwards arrowhead
- 1FBB1  INVERSE CHECK MARK
→ 2713  check mark
- 1FBB2  LEFT HALF RUNNING MAN
• paired with 1FBB3  , faces to the right
• the Apple II documentation refers to these characters as "Running Man"
→ 1F3C3  runner
- 1FBB3  RIGHT HALF RUNNING MAN

Arrows

- 1FBB4  INVERSE DOWNWARDS ARROW WITH TIP LEFTWARDS
→ 21B2  downwards arrow with tip leftwards
→ 21B5  downwards arrow with corner leftwards
- 1FBB5  LEFTWARDS ARROW AND UPPER AND LOWER ONE EIGHTH BLOCK
- 1FBB6  RIGHTWARDS ARROW AND UPPER AND LOWER ONE EIGHTH BLOCK
- 1FBB7  DOWNWARDS ARROW AND RIGHT ONE EIGHTH BLOCK
- 1FBB8  UPWARDS ARROW AND RIGHT ONE EIGHTH BLOCK

Terminal graphic characters

- 1FBB9  LEFT HALF FOLDER
• paired with 1FBBA 
→ 1F4C1  file folder
→ 1F5C0  folder
- 1FBBA  RIGHT HALF FOLDER
- 1FBBB  VOIDED GREEK CROSS
→ 0023  number sign
→ 256C  box drawings double vertical and horizontal
→ 2719  outlined greek cross
→ 271A  heavy greek cross
→ 1F7A3  medium greek cross
- 1FBBC  RIGHT OPEN SQUARED DOT
→ 22A1  squared dot operator

Negative terminal graphic characters

The glyphs for these "negative" characters do not necessarily extend to the edges of the character cell.

- 1FBBD  NEGATIVE DIAGONAL CROSS
• diagonals extend past the corners of the box, unlike in 274E 
→ 2573  box drawings light diagonal cross
→ 274E  negative squared cross mark
- 1FBBE  NEGATIVE DIAGONAL MIDDLE RIGHT TO LOWER CENTRE
- 1FBBF  NEGATIVE DIAGONAL DIAMOND

Terminal graphic characters

- 1FBC0  WHITE HEAVY SALTIRE WITH ROUNDED CORNERS
→ 274C  cross mark
→ 1F5D9  cancellation x
→ 1F7AC  heavy saltire

- 1FBC1  LEFT THIRD WHITE RIGHT POINTING INDEX
 • glyph part, combined with 1FBC2  and 1FBC3 
 → 261E  white right pointing index
- 1FBC2  MIDDLE THIRD WHITE RIGHT POINTING INDEX
- 1FBC3  RIGHT THIRD WHITE RIGHT POINTING INDEX
- 1FBC4  NEGATIVE SQUARED QUESTION MARK
 • glyph does not necessarily extend to the edges of the character cell
 → 003F  question mark
 → 2BD1  uncertainty sign
 → FFFD  replacement character
- 1FBC5  STICK FIGURE
 → 1F6B9  mens symbol
- 1FBC6  STICK FIGURE WITH ARMS RAISED
- 1FBC7  STICK FIGURE LEANING LEFT
- 1FBC8  STICK FIGURE LEANING RIGHT
- 1FBC9  STICK FIGURE WITH DRESS
 → 1F6BA  womens symbol
- 1FBCA  WHITE UP-POINTING CHEVRON
 → 21E7  upwards white arrow
 → 2302  house
 → 1F835  upwards finger-post arrow

Terminal graphic characters

- 1FBCB  WHITE CROSS MARK
- 1FBCC  RAISED SMALL LEFT SQUARE BRACKET
- 1FBCE  BLACK SMALL UP-POINTING CHEVRON

Block elements

- 1FBCE  LEFT TWO THIRDS BLOCK
- 1FBCF  LEFT ONE THIRD BLOCK

Character cell diagonals

- 1FBD0  BOX DRAWINGS LIGHT DIAGONAL MIDDLE RIGHT TO LOWER LEFT
- 1FBD1  BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE LEFT
- 1FBD2  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE RIGHT
- 1FBD3  BOX DRAWINGS LIGHT DIAGONAL MIDDLE LEFT TO LOWER RIGHT
- 1FBD4  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO LOWER CENTRE
- 1FBD5  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO LOWER RIGHT
- 1FBD6  BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO LOWER CENTRE
- 1FBD7  BOX DRAWINGS LIGHT DIAGONAL UPPER CENTRE TO LOWER LEFT
- 1FBD8  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE CENTRE TO UPPER RIGHT
- 1FBD9  BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE CENTRE TO LOWER RIGHT
- 1FBDA  BOX DRAWINGS LIGHT DIAGONAL LOWER LEFT TO MIDDLE CENTRE TO LOWER RIGHT
- 1FBDB  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE CENTRE TO LOWER LEFT
- 1FBDC  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO LOWER CENTRE TO UPPER RIGHT
- 1FBDD  BOX DRAWINGS LIGHT DIAGONAL UPPER RIGHT TO MIDDLE LEFT TO LOWER RIGHT
- 1FBDE  BOX DRAWINGS LIGHT DIAGONAL LOWER LEFT TO UPPER CENTRE TO LOWER RIGHT
- 1FBDF  BOX DRAWINGS LIGHT DIAGONAL UPPER LEFT TO MIDDLE RIGHT TO LOWER LEFT

Geometric shapes

- 1FBE0  TOP JUSTIFIED LOWER HALF WHITE CIRCLE
- 1FBE1  RIGHT JUSTIFIED LEFT HALF WHITE CIRCLE
- 1FBE2  BOTTOM JUSTIFIED UPPER HALF WHITE CIRCLE
- 1FBE3  LEFT JUSTIFIED RIGHT HALF WHITE CIRCLE
- 1FBE4  UPPER CENTRE ONE QUARTER BLOCK
- 1FBE5  LOWER CENTRE ONE QUARTER BLOCK
- 1FBE6  MIDDLE LEFT ONE QUARTER BLOCK
- 1FBE7  MIDDLE RIGHT ONE QUARTER BLOCK
- 1FBE8  TOP JUSTIFIED LOWER HALF BLACK CIRCLE
- 1FBE9  RIGHT JUSTIFIED LEFT HALF BLACK CIRCLE
- 1FBEA  BOTTOM JUSTIFIED UPPER HALF BLACK CIRCLE
- 1FBEB  LEFT JUSTIFIED RIGHT HALF BLACK CIRCLE
- 1FBE0  TOP RIGHT JUSTIFIED LOWER LEFT QUARTER BLACK CIRCLE
- 1FBED  BOTTOM LEFT JUSTIFIED UPPER RIGHT QUARTER BLACK CIRCLE
- 1FBE0  BOTTOM RIGHT JUSTIFIED UPPER LEFT QUARTER BLACK CIRCLE
- 1FBEE  TOP LEFT JUSTIFIED LOWER RIGHT QUARTER BLACK CIRCLE

Segmented digits

- 1FBF0  SEGMENTED DIGIT ZERO
 ≈ 0030 0 digit zero
- 1FBF1  SEGMENTED DIGIT ONE
 ≈ 0031 1 digit one
- 1FBF2  SEGMENTED DIGIT TWO
 ≈ 0032 2 digit two
- 1FBF3  SEGMENTED DIGIT THREE
 ≈ 0033 3 digit three
- 1FBF4  SEGMENTED DIGIT FOUR
 ≈ 0034 4 digit four
- 1FBF5  SEGMENTED DIGIT FIVE
 ≈ 0035 5 digit five
- 1FBF6  SEGMENTED DIGIT SIX
 ≈ 0036 6 digit six
- 1FBF7  SEGMENTED DIGIT SEVEN
 ≈ 0037 7 digit seven
- 1FBF8  SEGMENTED DIGIT EIGHT
 ≈ 0038 8 digit eight
- 1FBF9  SEGMENTED DIGIT NINE
 ≈ 0039 9 digit nine

Terminal graphic character

- 1FBFA  ALARM BELL SYMBOL
 → 237E  bell symbol
 → 1F514  bell